FUSE
Special devices
Electronic
Adjustable Fuse



FUSE is a 4-channel electronic current limiter created for LED strips protection and safe operation. The device is housed in a plastic DIN-rail mountable box and features a small OLED display offering real-time current measurement on each channel. Its main function is to protect the connected devices against overvoltage, undervoltage, overcurrent, and short-circuit. Additionally, FUSE provides information about device temperature and voltage on input, offering you a simple overview of the status of the system.

Working voltage range: 12-48V
Adjustable current limiter range: 0.6-5A
Manual/Auto reset mode:

- MANUAL - when a fault condition is discovered in the circuit, the RESET button needs to be pressed manually to restart operation;
- AUTO - when a fault condition is discovered in the circuit, the device performs auto retry after a set delay and checks if the fault condition is still present; operation is automatically restarted when the fault condition is removed.

Fault LED indicators
Display orientation rotation switch

SRS Group s.r.o reserves the right to make changes to the equipment described in this manual/datasheet without prior notice. (E&OE). © SRS Group s.r.o

SRS Group s.r.o.
Pri majeri 4, 831 07 Bratislava, Slovakia
phone: +421 232 661 800, email: sales@srs-group.com, www.srs-group.com